

GPRS/MMS Settings for Windows-based Handsets

Introduction

Our OTA module can find the make and model of Subscribers' handset and send them the related GPRS and MMS setting notification, via SMS. Subscribers will be able to use the services, after saving the received configurations on their handsets.

Note that some handsets are not supported by OTA. These types of handsets (i-mate, HP, htc, etc.) should be configured manually. In order to be able to use the MMS, subscriber's GPRS settings need to be configured first.

Instructions

For the handset types that are not recognized by OTA, the following manual configuration process should be followed:

GPRS setting:

- Go to "Start menu"
- Select "Setting"
- On the blue bar (Located in the bottom of the page), select "Connections"
- Go to "Connections"
- On "Manage existing connections"
- Go to General tab, enter a name "Iracell-internet"
- Go to Modem tab and select "New" (Located in the bottom of the page)
- Capture a name and select "Cellular Line (GPRS)" from drop down menu
- Go to Next
- Use "mtnirancell" as a access point name
- Go back to connection and on My Work Network, go to "Edit my proxy server"
- Choose the proxy settings from below bar and select "advance"
- Click on "HTTP", enter "10.131.26.138" on proxy server and "8080" for port
- Click on "WAP", enter "10.131.26.138" on proxy server and "9201" for port
- The setting configuration is completed now. Please go back to Start Menu and find Internet Explorer

MMS setting:

- Go to "Start Menu"
- Choose "Messaging"
- Go to Menu (Located in the bottom of the page)
- Go to MMS Configuration
- Find "Server" (Located in the bottom of the page)
- Select "New" and enter the below details:
 - Server Name: Iracell-MMS
 - Gate way: <http://10.131.26.138>
 - Port number: 8080
 - Server address: <http://mms:8002>
 - Connect via: Iracell-internet
 - Sending size limitation: 250K
 - WAP version: WAP 2.0